

Fender - Hammond Transformer Chart



Model Name	Model	POWER		OUTPUT		CHOKE		REVERB	
		Fender	Hammond	Fender	Hammond	Fender	Hamond	Fender	Hammond
Bandmaster	6G7A	67233		45217		125C1A	194B	N/A	
	AA763	125P7D	290EEX	125A6A	1750J/1760J	125C1A	194B	N/A	
	AC568	125P7D	290EEX	125A6A	1750J/1760J	125C1A	194B	N/A	
Bandmaster Reverb	AA270	125P5D	290DEX	125A6A	1750J/1760J	125C1A	194B	22921	1750A
	AA768	125P5D	290DEX	125A6A	1750J/1760J	125C1A	194B	22921	1750A
	AA1069	125P5D	290DEX	125A6A	1750J/1760J	125C1A	194B	22921	1750A
Bassman 4X10	5F6	8087		45249		14684		N/A	
	5F6A	8087		45249		14684		N/A	
	6G6	125P5A		125A5A		125C1A	194B	N/A	
	6G6A	125P7A		125A13A	1750M/1750L/1760L	125C1A	194B	N/A	
	AA270	125P7D	290EEX	125A13A	1750M/1750L/1760L	125C1A	194B	N/A	
	AA864	125P7D	290EEX	125A13A	1750M/1750L/1760L	125C1A	194B	N/A	
	AB165	125P7D	290EEX	125A13A	1750M/1750L/1760L	125C1A	194B	N/A	
	AC568	125P7D	290EEX	125A13A	1750M/1750L/1760L	125C1A	194B	N/A	
Champ	AA764	125P1B		125A35A	1750C/1760C	N/A		N/A	
Concert	6G12	67233		45249		125C1A	194B	N/A	
	AB763	125P7D	290EEX	125A9A	1750K	125C1A	194B	N/A	
Deluxe and Deluxe Reverb	6G3	125P2A		125A1A	1750H/1760H	N/A		N/A	
	AA763	125P23B	290BEX/291BEX	125A1A	1750H/1760H	125C3A	194A	22921	1750A
	AB868	125P23B	290BEX/291BEX	125A1A	1750H/1760H	125C3A	194A	22921	1750A
Harvard	6G10	125P1A		125A2A	1750H/1760H	N/A		N/A	
Princeton, Princeton Reverb	5F2A	66079		265		N/A		N/A	
	AA1164	125P1B	290AEX/291AEX	125A10B	1750E/1760E	N/A		22921	1750A
	B1270	125P1B	290AEX/291AEX	125A20B	1750A	N/A		22921	1750A
Pro and Pro Reverb	5C5	6516		1846		NA/		N/A	
	5D5	6516		1846		NA/		N/A	
	5E5A	6516		1846		NA/		N/A	
	6G5A	125P7D	290EEX	125A7A		125C1A	194B	N/A	
	AB763	125P5D	290DEX	125A7A		125C1A	194B	22921	1750A
	AA270	125P5D	290DEX	125A6A	1750J/1760J	125C1A	194B	22921	1750A
	AA1069	125P5D	290DEX	125A6A	1750J/1760J	125C1A	194B	22921	1750A

Fender - Hammond Transformer Chart



Model Name	Model	POWER		OUTPUT		CHOKE		REVERB	
		Fender	Hammond	Fender	Hammond	Fender	Hamond	Fender	Hammond
Reverb Unit	6G15	68319		NA		125C3A	194A	125A12A	
	6G15	125P24A		N/A		125C3A	194A	125A12A	
Showman	6G14	67233		45550		125C1A	194B	N/A	
	AA763	125P34A	290FX/291FX	125A30A		125C1A	194B	N/A	
Dual Showman	AB763	125P34A	290FX/291FX	125A29A	1750W/1760W	125C1A	194B	N/A	
Super and Super reverb	6G4	8087		45216		125C1A	194B	N/A	
	6G4A	125P7A		125A6A	1750J/1760J	125C1A	194B	N/A	
	AB563	125P5D	290DEX	125A9A	1750K	125C1A	194B	22921	1750A
	AA763	125P5D	290DEX	125A9A	1750K	125C1A	194B	22921	1750A
	AB763	125P5D	290DEX	125A9A	1750K	125C1A	194B	22921	1750A
Tremolux	AA270	125P5D	290DEX	125A9A	1750K	125C1A	194B	22921	1750A
	5G9	8160		108		14684		N/A	
	6G9	125P6A		45217		125C1A	194B	N/A	
	6G9A	125P6A		45217		125C1A	194B	N/A	
	6G9B	68409		125A6A	1750J/1760J	125C3A		N/A	
Twin and Twin Reverb	AB763	125P26A	290CEX	125A6A	1750J/1760J	125C3A		22921	1750A
	5G8A	7993		45268		14684		N/A	
	6G8	67233		45548		125C1A	194B	N/A	
	AB763	125P34A	290FX/291FX	125A29A	1750W/1760W	125C1A	194B	22921	1750A
	AC568	125P34A	290FX/291FX	125A29A	1750W/1760W	125C1A	194B	22921	1750A
	AA769	125P34A	290FX/291FX	125A29A	1750W/1760W	125C1A	194B	22921	1750A
Twin Reverb 7591 Tubes	AA270	125P34A	290FX/291FX	125A29A	1750W/1760W	125C1A	194B	22921	1750A
	AB763	125P19A		125A18A		125C1A	194B	22921	1750A
Vibrolux and Vibrolux Reverb	6G11	125P6A		45217		125C3A	194A	N/A	
	6G11A	68409		125A7A		125C3A	194A	N/A	
	AB763	125P26A	290CEX	125A7A		125C3A	194A	22921	1750A
	AA965	125P26A	290CEX	125A6A	1750J/1760J	125C3A	194A	22921	1750A
	AB568	125P26A	290CEX	125A6A	1750J/1760J	125C3A	194A	22921	1750A
Vibroverb	6G16	125P6A		45217		125C1A	194B	22921	1750A
	AA763	125P5D	290DEX	125A7A		125C1A	194B	22921	1750A